

IPS INVERTER VOLT POLSKA

IPS 4000 R 12/24V

The inverter **IPS 4000 R 12/24V** is designed to power electrical equipment that requires AC 230V from batteries and car installations with DC 12/24V. It is basically used in vehicles and in places where there is no possibility of direct connection to the power grid.

The main features:

The inverter IPS produces **modified sine wave** at its output. In this way, the device can power **resistive-resistance devices** such as laptops, chargers etc.

It also enables to reduce the price and increase the reliability of the entire device.

Possibility of remote on/off switching of the device.

The devices powered by IPS 4000 R 12/24V?

- Laptops
- Chargers
- Electronic devices
- Electric kettles
- Televisions
- RTV equipment
- Audio-video equipment

Technical data:

| MODEL | 4000 12V | 4000 24V |
|-----------------------------------|---|----------------|
| Max power | 4000VA | 4000VA |
| Continuous power | 2000W | 2000W |
| Battery voltage | 12V | 24V |
| Input voltage | 12V: 10,5 V - 15,5 V 24V: 21 V - 31 V | |
| Output voltage | 225-235V | |
| Output voltage frequency | 50 Hz (+-2Hz) | |
| Full load efficiency | ~ 92 % | |
| Undervoltage protection threshold | 12V: 10,7 V (+- 0,3 V) 24V: 21,4 V (+- 0,6 V) | |
| Working temperature | -10°C do 40°C | |
| Dimensions | 33x23x10cm | 33x23x10cm |
| Weight | 3960g | 3960g |
| Dimensions (single packaging) | 39,5x29,5x18cm | 39,5x29,5x18cm |
| Weight (single packaging) | 4800g | 4800g |
| Multipack dimensions | 41x31x38cm | 41x31x38cm |
| Multipack weight | 10,6kg | 10,6kg |

IPS 4000 R 12V:

INDEKS: 3IR400012R
EAN: 5904100450602

IPS 4000 R 24V:

INDEKS: 3IR400024R
EAN: 5904100450619



IPS 4000 R 12/24V



IPS 4000 R 12/24V



IPS 4000 R 12/24V