VP-2000 230V ↔ 110V (2000VA) VOLTAGE CONVERTER + SOFT-START

REGULAR RANGE

PRODUCT CODE
5K230110200

EAN
5903760240400

CATEGORY
Voltage stabilisers and converters

SUBCATEGORY
VP 110V/230V/110V voltage converters

PRODUCT PAGE
voltpolska.pl/produkty/vp-2000-230vac110vac-konwerter-napi...



ABOUT THE PRODUCT

VP-2000 230V ↔ 110V (2000VA) VOLTAGE CONVERTER + SOFT-START is a universal converter designed to reduce AC voltage from AC-230V to AC-110V or increase AC-110V to AC-230V. It is used to power devices originating from the USA and Japan.

The device's output voltage is 120 AC in accordance with current US standards. The converter is proportional, so the output voltage depends on the input voltage. The SOFT-START function limits the load during start-up.

The converter is equipped with a toroidal transformer, a metal housing with a convenient handle, and earthed input and output. It can power, among other things, chargers, shavers, players, household appliances such as the Kitchen AID Artisan food processor, and power tools: saws, drills, grinders and screwdrivers.

TECHNICAL SPECIFICATIONS

Electrical specifications	**Total power (instantaneous)**	2000 VA
	Input voltage	230 VAC (or 110 VAC)
	Output voltage	110 VAC (120 VAC according to US standards) or 230 VAC
	SOFT-START function	Yes
Equipment and connectors	**Output sockets (GWY)**	4x GWY
	Power cord	W set
Overall dimensions and weight	**Device dimensions**	218 x 168 x 138 mm
	Net weight	6,9 kg
	Individual package dimensions	280 x 215 x 180 mm
	Individual package weight	7,3 kg

VOLT POLSKA Sp. z o.o.

ul. Świemirowska 3, 81-877 Sopot
NIP 5851458032 | REGON 221142660
KRS 0000372066

voltpolska.pl
(58) 500-85-62
hurt@voltpolska.pl
pomoc@voltpolska.pl

GENERATED: 2026-10-30 16:06

PRODUCT GALLERY











VOLT POLSKA Sp. z o.o.

ul. Świemirowska 3, 81-877 Sopot
NIP 5851458032 | REGON 221142660
KRS 0000372066

voltpolska.pl
(58) 500-85-62
hurt@voltpolska.pl
pomoc@voltpolska.pl

This datasheet was generated automatically; technical data and images are for reference only and may change without notice. To the extent permitted by law, VOLT POLSKA accepts no liability for any errors or inaccuracies in this datasheet.